

Scan

Punch Led







Scan

Pun

Scan


Punch Led

Scan



LEFT

RIGHT



12db American Dj Punch Led Pro (7ch dmx)

4db American Dj Scan 250EX (5ch dmx)

1db American Dj Accu Fog 1000 (5ch dmx)

3db Led RGB (4ch dmx)

DMX address

Punch Led DMX (L-R) ----- 13,20,27,34,41,48,55,62,69,76,83,90

Scan 250EX DMX (L-R) --- 97,102,107,112

Accu Fog DMX ---117

Par Led ---129,133,137

American Dj Punch Led Pro (7ch dmx)

Channel Value Function

1. 0 - 255 RED 0% 100%
2. 0 - 255 GREEN 0% 100%
3. 0 - 255 BLUE 0% 100%
4. 0 - 7 NOTHING
8 - 255 COLOR MACRO
5. 0 - 15 NOTHING
16 - 255 STROBING/MACRO SPEED
6. 0 - 31 NOTHING
32 - 63 DIM BRIGHT
64 - 95 BRIGHT DIM
96 - 127 DIM BRIGHT DIM
128 - 159 COLOR MIXING
160 - 191 3 COLOR CHANGE
192 - 223 7 COLOR CHANGE
224 - 255 SOUND ACTIVE
7. 0 - 255 DIMMER 0% 100%

American Dj Scan 250EX (5ch dmx)

Channel Value Function

1. 0 - 255 PAN

2. 0 - 255 TILT

3. COLOR WHEEL

0 - 10 WHITE

11 - 21 RED

22 - 32 DEEP BLUE

33 - 43 GREEN 44 - 54 YELLOW

55 - 65 ORANGE

66 - 76 PINK

77 - 87 LIGHT BLUE

88 - 98 UV PURPLE

99 - 109 MAGENTA

110 - 120 ORANGE + RED

121 - 127 LIGHT BLUE + MAGENTA

128 - 255 RAINBOW EFFECT SLOW - FAST

4. GOBO WHEEL

0 - 11 OPEN

12 - 23 GOBO 1

24 - 35 GOBO 2

36 - 47 GOBO 3

48 - 59 GOBO 4

60 - 71 GOBO 5

72 - 83 GOBO 6

84 - 95 GOBO 7

96 - 107 GOBO 8

108 - 119 GOBO 9

120 - 127 GOBO 10

GOBO WHEEL ROTATION SLOW - FAST

5. SHUTTER/STROBE

0 - 7 BLACKOUT

8 - 15 SHUTTER OPEN

16 - 131 STROBING SLOW - FAST

132 - 247 GOBO SHAKE SLOW - FAST

248 - 255 SHUTTER OPEN

American Dj Accu Fog 1000(5ch dmx)

Channel Value Function

1. 0 - 255 PAN
2. 0 - 255 TILT
3. SPEED OF PAN/TILT MOVEMENT
 - 0 - 225 ADJUST MOVEMENT SPEED FAST SLOW
 - 226 - 255 NO FUNCTION
4. PUMP DURATION (FOG) TIME
 - 0 - 20 PUMP OFF
 - 21 - 255 PUMP ON
5. AUTO PROGRAM
 - 0 - 39 NO FUNCTION
 - 40 - 59 HEATER ON
 - 60 - 79 HEATER SWITCH OFF
 - 80 - 99 MOTOR RESET
 - 100 - 119 INTERNAL PROGRAM 1
 - 120 - 139 INTERNAL PROGRAM 2
 - 140 - 159 INTERNAL PROGRAM 3
 - 160 - 179 INTERNAL PROGRAM 4
 - 180 - 199 INTERNAL PROGRAM 5
 - 200 - 219 INTERNAL PROGRAM 6
 - 220 - 239 INTERNAL PROGRAM 7
 - 240 - 255 SOUND ACTIVE